

November 2019

Trade and Industry Information

700MHz Clearance Events

STV Region

Following a decision by Ofcom, spectrum in the 700MHz UHF band currently used for digital terrestrial television (DTT) is being reallocated for the development of future mobile services. Some DTT multiplexes will be moving to new broadcast frequencies as a result of this change.

Engineering work for the 700MHz Clearance Programme will take place at transmitters across the UK between 2017 - 2020. Freeview viewers (and those with other services that use Freeview channels, such as YouView) will need to retune their TV equipment when changes take place in their area. This document lists the currently announced clearance events for the STV region and will be updated as new information is released. Details of the changes to transmitters will also be reflected on our coverage checker at www.freeview.co.uk/help.

Note: Where multiplexes are moving we have included the current and future aerial group required to receive Freeview services. Digital UK recommends installers fitting new aerials use a wideband model where possible to accommodate future changes to broadcast frequencies.

2020

4 March 2020

Black Hill – Campbeltown and Blackwaterfoot relay stations only

Q3 2019

14 August 2019

Black Hill – some relay stations only

04 September 2019

Darvel – some relay stations only

11 September 2019

Black Hill – Uplawmoor relay station only

Q4 2019

27 November 2019

Angus – main station and some relays only

Previous Events

Q3 2017

26 July 2017

Bressay – some relay stations only

23 August 2017

Knockmore – main and some relay stations

Rumster Forest – main and some relay stations

6 September 2017

Rosemarkie – some relay stations only

20 September 2017

Eitshal – some relay stations only

Skriaig – some relay stations only

Q4 2017

4 October 2017

Torosay – main and some relay stations

Q3 2018

15 August 2018

Durris – main station and some relay stations

5 September 2018

Black Hill – main station and some relay stations

Craigkelly – some relay stations only

Darvel – main station and some relay stations

Rosneath – main station and some relay stations

19 September 2018

Black Hill – some relay stations only

Q4 2018

3 October 2018

Angus – main station and Dundee Menzieshill relay

Black Hill – main station and Cumbernauld Village relay

Craigkelly – main station and some relay stations

Durris – main station only

4 March 2020

The BLACK HILL transmitter group, serving Glasgow, central Scotland and parts of Edinburgh

Blackwaterfoot

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	43	46	50
		04.03.20	43	46	40

Power change: None

Campbeltown - changes also occurred on 5 September 2018

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
C/D	B	Current	39	57	53
		04.03.20	39	42	45

Power change: None

14 August 2019

The BLACK HILL transmitter group, serving Glasgow, central Scotland and parts of Edinburgh

Clachan

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	A	Current	43	46	40
		14.08.19	29	31	37

Power change: None

Easdale

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	A	Current	40	46	43
		14.08.19	29	31	37

Power change: the ERP will change from 2W to 7W for all multiplexes

Gigha Island

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	A	Current	41+	44	47
		12.06.19	29	31	37

Power change: None

Gigha Island

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	A	Current	41+	44	47
		14.08.19	29	31	37

Power change: None

South Knapdale

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	B	Current	60-	57	53
		14.08.19	39	42	45

Power change: the ERP will change from 300W to 500W for all multiplexes

South Knapdale HP

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
N/A	B	Current	-	-	-
		14.08.19	39	42	45

Power change: the ERP will launch at 20W for all multiplexes

4 September 2019

The DARVEL transmitter group, serving parts of central Scotland, Argyll and Bute

Dunure

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	A	Current	46	43	40
		04.09.19	32	34	35

Power change: None

Girvan - changes also occurred on 5 September 2018

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	50	31	37
		04.09.19	29	31	37

Power change: None

Troon

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	K	Current	49	58	54
		04.09.19	29	37	48

Power change: None

11 September 2019

The BLACK HILL transmitter group, serving Glasgow, central Scotland and parts of Edinburgh

Uplawmoor

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	49	58	54
		11.09.19	29	37	31

Power change: None

27 November 2019

The ANGUS transmitter group, serving Angus, Dundee, Perth and parts of Fife

Angus - changes also occurred on 3 October 2018

Current Aerial Group	Future Aerial Group		RF Channel					
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)	COM4 (SDN)	COM5 (ARQA)	COM6 (ARQB)
CD	T	Current	60-	53	57	54	58	49
		27.11.19	39	42	45	33	36	48

	RF Channel		
	COM7 (NUK7)	COM8 (NUK8)	LOC1
Current	55	56	48
27.11.19	55	56	34

Power change: None

Auchtermunchty

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	A	Current	39	42	45
		27.11.19	23	26	30

Power change: None

Balmullo

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	A	Current	39	42	45
		27.11.19	32	34	35

Power change: None

Balnaguard

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	39	45	42
		27.11.19	40	43	46

Power change: None

Blair Atholl

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	43	46	50
		27.11.19	43	46	40

Power change: None

Crieff

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
A	A	Current	23	29	26
		27.11.19	23	30	26

Power change: None

Cupar

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	41+	47	44
		27.11.19	41	47	44

Power change: None

Dunkeld

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	41+	47	44
		27.11.19	41	47	44

Power change: None

Dunkeld Town

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
A	A	Current	23	29	26
		27.11.19	23	30	26

Power change: None

Grandtully

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	49	54	58
		27.11.19	32	34	35

Power change: None

Killin HP & VP

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	39	42	45
		27.11.19	40	43	46

Power change: Killin HP – the ERP will change from 4W to 7W for all multiplexes, Killin VP – the ERP will change from 23W to 40W for all multiplexes

Lochearnhead

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	49	54	58
		27.11.19	32	34	35

Power change: None

Perth

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	A	Current	39+	42+	45+
		27.11.19	29	31	37

Power change: None

St Fillans

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	47	41+	44
		27.11.19	47	41	44

Power change: None

Strathallan

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	A	Current	39	42	45
		27.11.19	29	31	37

Power change: None

Tay Bridge

Current Aerial Group	Future Aerial Group		RF Channel			
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)	LOC1
B	K	Current	41+	47	44	51
		27.11.19	41+	47	44	32

Power change: None

26 July 2017

The BRESSAY transmitter group, serving the Shetland Islands

Baltasound

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	46-	43-	50
		Future	46-	43-	40

Power change: None

Scalloway

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	50	59	55
		Future	32	34	35

Power change: None

Swinister

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	50	59	55
		Future	32	34	35

Power change: None

Voe

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	B	Current	57	60	53
		Future	41	44	47

Power change: None

Weisdale

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	Wideband	Current	58	49	54
		Future	33	36	48

Power change: None

23 August 2017

The KNOCKMORE transmitter group, serving Morayshire, Strathspey and part of Easter Ross

Knockmore

Current Aerial Group	Future Aerial Group		RF Channel					
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)	COM4 (SDN)	COM5 (ARQA)	COM6 (ARQB)
Wideband	Wideband	Current	26	23	29	53	57	60-
		Future	31	37	29	33	36	48

Power change: None

Avoch

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	58	54	49
		Future	32	34	35

Power change: None

Balblair Wood

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	50	59	55
		Future	32	34	35

Power change: None

Craigellachie

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	B	Current	58	49	54
		Future	40	43	46

Power change: None

23 August 2017

The RUMSTER FOREST transmitter group, serving Caithness and North Sutherland

Rumster Forest

Current Aerial Group	Future Aerial Group		RF Channel					
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)	COM4 (SDN)	COM5 (ARQA)	COM6 (ARQB)
Wideband	Wideband	Current	27	24	21+	30-	59	55
		Future	27	24	21+	32	34	35

Power change: None

Ben Tongue

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	45	49	42
		Future	45	39	42

Power change: None

Durness

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	B	Current	57	53	60
		Future	41	44	47

Power change: None

Thurso

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	B	Current	57	60	53
		Future	41	44	47

Power change: None

6 September 2017

The ROSEMARKIE transmitter group, serving Inverness and the Great Glen

Fodderty

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	B	Current	58	49	54
		Future	41	44	47

Power change: None

Inverness

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	50	55	59
		Future	29	31	37

Power change: None

20 September 2017

The EITSHAL transmitter group, serving Lewis, Wester Ross, North West Sutherland and parts of Harris and Skye

Badachro

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	46	43	50
		Future	46	43	40

Power change: None

Kinlochbervie HP & VP

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	46	43	50
		Future	46	43	40

Power change: None

Lochinver

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	46	43	50
		Future	46	43	40

Power change: None

Staffin

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	45	49	42
		Future	45	39	42

Power change: None

Ullapool

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	45	49	42
		Future	45	39	42

Power change: None

20 September 2017

The SKRIAIG transmitter group, serving Skye, Harris, North Uist, Benbecula, South Uist and part of Barra

Daliburgh

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	B	Current	60	57	53
		Future	39	42	45

Power change: None

Inverarish

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	46	43	50
		Future	46	43	40

Power change: None

Kilbride South Uist

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	A	Current	39	45	42
		Future	32	34	35

Power change: None

Penifiler

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	45	49	42
		Future	45	39	42

Power change: None

Scoval HP & VP

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	B	Current	50	59	55
		Future	40	43	46

Power change: None

Tarbert Harris

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	A	Current	45	39	42
		Future	32	34	35

Power change: None

4 October 2017

The TOROSAY transmitter group, serving South West Highlands and Islands

Torosay

Current Aerial Group	Future Aerial Group		RF Channel					
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)	COM4 (SDN)	COM5 (ARQA)	COM6 (ARQB)
A	A	Current	28	25	22	23	26	29
		Future	28	25	22	23	26	30

Power change: None

Acharacle

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	46	43	50
		Future	46	43	40

Power change: None

Arisaig

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
A	A	Current	26	23	29
		Future	26	23	30

Power change: None

Ballachulish

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
A	A	Current	23	29	26
		Future	23	30	26

Power change: None

Bellanoch

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	45	42	49
		Future	41	44	47

Power change: None

Cow Hill

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	46	43	50
		Future	46	43	40

Power change: None

Fiunary

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	46	43	50
		Future	46	43	40

Power change: None

Glengorm

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	A	Current	44+	41+	47+
		Future	29	31	37

Power change: None

Kilmelford

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	50	59	55
		Future	29	31	37

Power change: None

Kinlochleven

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	59	55	50
		Future	29	31	37

Power change: None

Loch Feochan

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	54	49	58
		Future	32	34	35

Power change: None

Mallaig

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	46-	43-	50
		Future	46-	43-	40

Power change: None

Onich HP & VP

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	49	54	58
		Future	32	34	35

Power change: None

Strontain

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	39	45	42
		Future	39	45	42

Power change: the ERP will change from 3W to 6W for all multiplexes

Taynuilt

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	46	43	50
		Future	46	43	40

Power change: None

Tayvallich

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	46	43	50
		Future	46	43	40

Power change: None

15 August 2018

The DURRIS transmitter group, serving Aberdeen and Aberdeenshire

Durris - further changes to occur on 3 October 2018

Current Aerial Group	Future Aerial Group		RF Channel					
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)	COM4 (SDN)	COM5 (ARQA)	COM6 (ARQB)
A	T	Current	28	25	22	23	26	29
		15.08.18	28	25	22	23	26	29

	RF Channel		
	COM7 (NUK7)	COM8 (NUK8)	LOC1
Current	32	35	30
15.08.18	55	56	41

Power change: None

Balgownie

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	46	43	50
		15.08.18	46	43	40

Power change: None

Braemar

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	45	42	49
		15.08.18	45	42	39

Power change: None

Brechin

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	46	43	50
		15.08.18	46	43	40

Power change: None

Gartley Moor

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	B	Current	58	49	54
		15.08.18	41	44	47

Power change: None

Gourdon

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	50	59	55
		15.08.18	32	34	35

Power change: None

Peterhead

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	K	Current	50	59	55
		15.08.18	33	36	48

Power change: None

Tomintoul

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	46	43	50
		15.08.18	46	43	40

Power change: None

Tullich

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	50	59	55
		15.08.18	32	34	35

Power change: None

5 September 2018

The BLACK HILL transmitter group, serving Glasgow, central Scotland and parts of Edinburgh

Black Hill - further changes to occur on 3 October 2018

Current Aerial Group	Future Aerial Group		RF Channel					
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)	COM4 (SDN)	COM5 (ARQA)	COM6 (ARQB)
B	T	Current	46	43	40	41+	44	47
		05.09.18	46	43	40	41+	44	47

	RF Channel		
	COM7 (NUK7)	COM8 (NUK8)	LOC1
Current	32	35	51
05.09.18	55	56	51

Power change: None

Glasgow West Central

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	50	59	55
		05.09.18	21	24	27

Power change: None

Kelvindale

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	52	56	48
		05.09.18	29	31	37

Power change: None

Killearn

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	50	59	55
		05.09.18	32	34	35

Power change: None

Kirkfieldbank

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	50	59	55
		05.09.18	29	31	37

Power change: None

Netherton Braes

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
A	A	Current	27	24	21+
		05.09.18	23	26	29

Power change: the ERP will change from 2W to 4W for PSB3

Rothesay Town

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	50	59	55
		05.09.18	29	31	37

Power change: None

5 September 2018

The CRAIGKELLY transmitter group, serving Lothian, parts of Edinburgh and parts of Fife

Aberfoyle - further changes to occur on 3 October 2018

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	55	50	59
		05.09.18	32	50	59

Power change: the ERP will change from 18W to 33W for PSB1

Cannongate HP & VP - further changes to occur on 3 October 2018

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	55	50	59
		05.09.18	35	50	59

Power change: None

Newbattle - further changes to occur on 3 October 2018

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	B	Current	50	59	55
		05.09.18	50	59	47

Power change: None

5 September 2018

The DARVEL transmitter group, serving parts of central Scotland, Argyll and Bute

Darvel

Current Aerial Group	Future Aerial Group		RF Channel					
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)	COM4 (SDN)	COM5 (ARQA)	COM6 (ARQB)
A	T	Current	22-	25	28	23	26	29
		05.09.18	22-	25	28	32	34	35

	RF Channel		
	COM7 (NUK7)	COM8 (NUK8)	LOC1
Current	31	37	30
05.09.18	55	56	31

Power change: None

Ayr South

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	A	Current	45	39	42
		05.09.18	26	29	37

Power change: the ERP will change from 2W to 4W for all multiplexes

Bowmore HP & VP

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	A	Current	47	41+	44
		05.09.18	29	31	37

Power change: None

Campbeltown - further changes to occur in Q1 2020

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	B	Current	60	57	53
		05.09.18	39	57	53

Power change: None

Carradale

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	44	41+	47
		05.09.18	44	41+	47

Power change: the ERP will change from 5W to 12W for all multiplexes

Catrine

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	B	Current	50	59	55
		05.09.18	39	42	45

Power change: None

Claonaig

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	50	59	55
		05.09.18	29	31	37

Power change: the ERP will change from 15W to 30W for all multiplexes

Girvan - further changes to occur in Q3 2019

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	50	59	55
		05.09.18	50	31	37

Power change: None

Kirkmichael

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	45	49	42
		05.09.18	45	39	42

Power change: the ERP will change from 4W to 9W for all multiplexes

Lethanhill

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	K	Current	60	57	53
		05.09.18	33	36	48

Power change: None

Lochgoilhead

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	B	Current	53	57	60
		05.09.18	41	44	47

Power change: None

Lochwinnoch

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	K	Current	60	57	53
		05.09.18	33	36	48

Power change: None

Millburn Muir

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	A	Current	42	45	39
		05.09.18	29	31	37

Power change: None

Portnahaven

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
A	A	Current	23	29	26
		05.09.18	23	30	26

Power change: None

5 September 2018

The ROSNEATH transmitter group, serving Rosneath

Rosneath HP & VP

Current Aerial Group	Future Aerial Group		RF Channel					
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)	COM4 (SDN)	COM5 (ARQA)	COM6 (ARQB)
CD	K	Current	49	58	54	53	57	60-
		05.09.18	39	42	45	33	36	48

Power change: None

Ardnadam

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	A	Current	42	45	39
		05.09.18	29	31	37

Power change: None

Garelochhead

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	A	Current	42	45	39
		05.09.18	29	31	37

Power change: None

19 September 2018

The BLACK HILL transmitter group, serving Glasgow, central Scotland and parts of Edinburgh

Abington

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	B	Current	60	57	53
		19.09.18	39	42	45

Power change: None

Bridge Of Allan

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
A	A	Current	26	23	29
		19.09.18	26	23	30

Power change: None

Cathcart

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	B	Current	60	57	53
		19.09.18	39	42	45

Power change: None

Deanston

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	B	Current	60	53	57
		19.09.18	39	42	45

Power change: None

Dollar

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	49	58	54
		19.09.18	32	34	35

Power change: None

Glespin

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	49	58	54
		19.09.18	23	26	30

Power change: None

Haddington

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	K	Current	49	58	54
		19.09.18	33	36	48

Power change: the ERP will change from 4W to 8W for all multiplexes

Kirkconnel

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	49	58	54
		19.09.18	29	31	37

Power change: None

Largs

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	A	Current	45	58	54
		19.09.18	29	31	37

Power change: the ERP will change from 5W to 10W for all multiplexes

Leadhills

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	49	58	54
		19.09.18	32	34	35

Power change: None

Millport

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	49	58	54
		19.09.18	32	34	35

Power change: None

New Cumnock

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	43	46	50
		19.09.18	43	46	40

Power change: None

Tighnabruaich

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	45	49	42
		19.09.18	40	43	46

Power change: None

Tillicoultry

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	B	Current	60	57	53
		19.09.18	39	42	45

Power change: None

3 October 2018

The ANGUS transmitter group, serving Angus, Dundee, Perth and parts of Fife

Angus - further changes to occur in Q4 2019

Current Aerial Group	Future Aerial Group		RF Channel					
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)	COM4 (SDN)	COM5 (ARQA)	COM6 (ARQB)
CD	T	Current	60-	53	57	54	58	49
		03.10.18	60-	53	57	54	58	49

	RF Channel		
	COM7 (NUK7)	COM8 (NUK8)	LOC1
Current	31	37	48
03.10.18	55	56	48

Power change: None

Dundee Menzieshill

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
A	A	Current	23	29	26
		03.10.18	23	30	26

Power change: None

3 October 2018

The BLACK HILL transmitter group, serving Glasgow, central Scotland and parts of Edinburgh

Black Hill - change also occurred on 05 September 2018

Current Aerial Group	Future Aerial Group		RF Channel					
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)	COM4 (SDN)	COM5 (ARQA)	COM6 (ARQB)
B	T	Current	46	43	40	41+	44	47
		03.10.18	46	43	40	41+	44	47

	RF Channel		
	COM7 (NUK7)	COM8 (NUK8)	LOC1
Current	55	56	51
03.10.18	55	56	30

Power change: the ERP will change from 5kW to 10kW for LOC1

Cumbernauld Village

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	K	Current	49	58	54
		03.10.18	33	36	48

Power change: None

3 October 2018

The CRAIGKELLY transmitter group, serving Lothian, parts of Edinburgh and parts of Fife

Craigkelly

Current Aerial Group	Future Aerial Group		RF Channel					
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)	COM4 (SDN)	COM5 (ARQA)	COM6 (ARQB)
K	T	Current	27	24	21+	42	45	39+
		03.10.18	27	24	21+	29	31	37

	RF Channel		
	COM7 (NUK7)	COM8 (NUK8)	LOC1
Current	33	34	30
03.10.18	55	56	32

Power change: None

Aberfoyle - change also occurred on 05 September 2018

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	32	50	59
		03.10.18	32	34	35

Power change: the ERP will change from 18W to 33W for PSB2 and PSB3

Cannogate HP & VP - change also occurred on 05 September 2018

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	35	50	59
		03.10.18	35	34	33

Power change: None

Grangemouth

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	B	Current	53	60	57
		03.10.18	39	42	45

Power change: None

Kinross

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	59	50	55
		03.10.18	32	34	35

Power change: None

Newbattle - change also occurred on 05 September 2018

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	B	Current	50	59	47
		03.10.18	41	44	47

Power change: None

Penicuik

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	B	Current	54	49	58
		03.10.18	39	42	45

Power change: None

West Linton

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
A	A	Current	29	23	26
		03.10.18	30	23	26

Power change: None

3 October 2018

The DURRIS transmitter group, serving Aberdeen and Aberdeenshire

Durris - change also occurred on 15 August 2018

Current Aerial Group	Future Aerial Group		RF Channel					
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)	COM4 (SDN)	COM5 (ARQA)	COM6 (ARQB)
A	T	Current	28	25	22	23	26	29
		03.10.18	28	25	22	23	26	30

	RF Channel		
	COM7 (NUK7)	COM8 (NUK8)	LOC1
Current	55	56	41
03.10.18	55	56	41

Power change: None